



Information Sheet



Pocket Toner® NX8 Audio/Video Pro Kit

Simply the best way to identify and test multiple speaker wires and video cables

What's In the Kit:

- | | |
|--------------------------------------|---------------------------------------|
| Pocket Toner® NX8 | RCA female adapter |
| 8 ID caps | F-female coupler (F-81) |
| 8 2-wire clip adapters | F-male coupler (F-71) |
| Alligator clips & RCA male adapter | F-female coupler (<i>Speed 81™</i>) |
| Alligator clips & RCA female adapter | F-male push-on adapter |
| 8 RCA Male Adapters | AAA battery |
| | Deluxe case with belt clip |



Imagine testing a surround sound system for continuity and short circuits with speed and efficiency. With the PTNX8 Audio / Video Pro and its specially designed adapters audio/video installations and troubleshooting are a breeze.


PTNX8 is the best tone and tag tool for testing continuity, shorts, 50-75 Ω termination, and polarity—on eight cables at once! Simply place each of the numbered ID caps on the remote ends of the cables (either speaker wires or coaxial cable) to test then connect the main unit to the other end of the test cables one at a time. If there is continuity, the green LED on the ID cap will light and the main unit will show the ID cap's number (1-8) on its digital display. In addition, the audible indicator in the main unit will emit a short tone. PTNX8 also tests for the presence of both AC and DC voltages from 6v-48v.

FEATURES

- Low-voltage circuit protection (6v -48v) in main unit, toner unit & ID caps
- Patented Gale Corporation adapters to test any wire or cable
- 8-Segment LED displays 5 different test results
- Audible indicators in both Main Unit & detachable Toner Unit
- LED indicators on all ID caps indicate continuity
- Main Unit “beeps” when line condition changes
- Test up to 8 cables at once
- Bi-gender Toner Unit w/removable *Speed 81™* coupler
- Removable push-on F-type connector
- Nickel-plated brass connection fittings
- Lightweight and durable, anodized aluminum construction
- Push-button power switch w/dust seal
- Auto shut-off feature extends battery life
- Key high-wear parts are replaceable
- Uses 1 standard AAA battery
- One-year limited warranty



Test Result Display	
	Blinking [-] indicates an open circuit
	Blinking [5] indicates a short
	Solid [7] indicates continuity with either a 50-75 ohm ID cap or the toner unit
	A solid matching number indicates continuity with one of the 8 ID caps
	Blinking [⚡] indicates AC voltage (>6 volts)
	Solid [⚡] indicates DC voltage (>6 volts)



Gale Corporation

P.O. Box 417280 Sacramento, CA 95841 | 888.566.5728 | info@galecorp.com | www.galecorp.com

Part #: PTNX8-AV-PRO
Price: \$139.49

